

Description

The *Smoke Detector* is a device which connects with *HCS EMD*.

Through *inSentry*, user can monitor it if there is any situation of *Smoke*.

Features

- New Design on minified Chamber makes so easy for maintenance.
- High luminous LED for light guiding design
- Detector has passed strict EMC test, which greatly eliminates false alarms caused by interference from nearby sources.
- Simple test method: Press test button to hear the alarm sound and confirm the unit is in normal condition.
- Easy installation: Install directly to proper location without any wiring.
- It is equipped with 9VDC battery, and optional 100-240VAC power plug is available.
- Optional relay output: COM. NO. NC.
- Optional series connection wiring can co-activate up to 20 detectors.



Approval

- ☒ EN 14604
- ☒ CE

PROPERTIES

Power	9V Battery
Sensitivity Setting	Comply to EN14604
Indicator	Standby: flash every 45 seconds Alarm: flash and beep continuously Battery abnormal: beeps and flash intermittently
Sound	90dB/M and above
Ambient Temperature	-10C to + 55C
Material	Fire-Proof Plastic
Dimensions	102 Diameter x 48mm Height
Weight	About 165g
Color	White
Optional Function	Type 1: 9V Battery Type 2: Includes signal transfer COM. N.O. N.C. Type 3: Type 2 + Type 4 Type 4: Build-in 110VAC or 220VAC plug

EFFECTIVE ALERT AREA

Building Height	Area Covered
Under 4M	150m ²
4-20M	75M ²

ORDERING INFORMATION

HCS P/N	Description
HCS-EMD-SD	HCS EMD Smoke Detector